
# PCPI xH/TETRA/...

Indoor Left or Right Hand Circularly Polarized Patch Antennas for mounting on Wall or Ceiling

#### **DESCRIPTION**

- Low-profile antenna for the 380 470 MHz band.
- PCPI xH/TETRA/... is a Left or Right Hand Circularly Polarized patch antenna for indoor use.
- Circular polarization is chosen to avoid out-of-phase signals.
- Reduces flutter considerably.
- Specially designed for closed rooms.
- Covers approx. 50 MHz with a radiation of approx. 7 dBic.
- The antennas are carefully sealed with a discreet cover.
- The connector is placed at one side to enable mounting close to a wall or a ceiling.
- Including mounting bracket.
- Connection also available on backside (see overleaf).



### STANDARD VERSION ORDERING DESIGNATIONS

TYPE	FREQUENCY	PRODUCT NO.
PCPI RH/TETRA/s-f	380 - 430 MHz	100000426
PCPI LH/TETRA/s-f	380 - 430 MHz	100000425
PCPI RH/TETRA/I-h	430 - 470 MHz	100000442
PCPI LH/TETRA/l-h	430 - 470 MHz	100000441
ACCESSORIES		
PATCH-WAMO		100000511

#### BC VERSION ORDERING DESIGNATIONS


TYPE	FREQUENCY	PRODUCT NO.
PCPI RH/TETRA/s-f-BC	380 - 430 MHz	100000468
PCPI LH/TETRA/s-f-BC	380 - 430 MHz	
PCPI RH/TETRA/I-h-BC	430 - 470 MHz	
PCPI LH/TETRA/I-h-BC	430 - 470 MHz	

### **SPECIFICATIONS**


ELETRICAL	
MODEL	PCPI xH/TETRA/
ANTENNA TYPE	Left or right hand circularly polarized patch antenna
FREQUENCY	380 - 470 MHz covered by two models
IMPEDANCE	Nom. 50 Ω
POLARIZATION	Circular
GAIN	Approx. 7 dBic
BANDWIDTH	≥ 50 MHz
HALF POWER BEAMWIDTH	Approx. 80° (H- and E-plane)
SWR	≤ 2
MAX. POWER	100 W
MECHANICAL	
TEMP. RANGE	-30° C → +75° C
CONNECTOR	N-female
COLOUR	Marine white
MATERIALS	Cover: ABS (white) Chassis: Aluminium
SIZE (L x W x H)	Approx. 345 x 345 x 60 mm / 13.58 x 13.58 x 2.36 in.
WEIGHT	Approx. 2.3 kg / 5.07 lb.
MOUNTING	For mounting on wall or ceiling ø5 mm / 0.20 in. (three holes) (see mounting details)




### MOUNTING DETAILS




### MOUNTING DETAILS BC VERSION




## MOUNTING DETAILS (PATCH-WAMO)



### TYPICAL GAIN AND SWR CURVES




### TYPICAL RADIATION PATTERN (E-PLANE)



This curve shows the radiation patterns in the vertical plane.

### TYPICAL RADIATION PATTERN (H-PLANE)



This curve shows the radiation patterns in the horizontal plane (horizontal coverage).



PROCOM A/S reserve the right to amend specifications without prior notice.

02/10/14

